

NOTES:

4. ALL COMPONENTS ARE SHOWN DE-ENERGIZED.
5. FOR SINGLE PHASE UNITS:
120/240, 3 WIRE-CONNECT POWER CABLES TO A AND C
120/ L-N, 2 WIRE-CONNECT POWER CABLES TO A AND NEUTRAL
6. A JUMPER IS CONNECTED BETWEEN TB2-2 AND TB2-3 WHEN USED WITH A GENSET WITH A POSITIVE START SIGNAL. A JUMPER IS CONNECTED BETWEEN TB2-2 AND TB2-1 WHEN USED WITH A GENSET WITH A NEGATIVE START SIGNAL.
7. CONTACT AVAILABLE ON OLD STYLE AUXILIARY CONTACT BLOCK ONLY.REFER TO DETAIL "A" TO DETERMINE WHICH STYLE BLOCK IS INSTALLED ON TRANSFER SWITCH. IF NEW STYLE BLOCK IS INSTALL CONTACT IS REPLACED BY A DIRECT CONNECTION.

LEGEND:

- K1(CC) NORMAL CLOSING COIL
K1(TC) NORMAL TRIP COIL
K2(CC) EMERGENCY CLOSING COIL
K2(TC) EMERGENCY TRIP COIL
S3 MANUAL OVERRIDE SWITCH
S12 TEST SWITCH
S14 INSTANT RETRANSFER SWITCH

