

# TECHNICAL SUPPORT

## Gas Engine Conversion

---

A certified GAS engine General Motors, Ford or Doosan are all set up the same.

**NG:** solenoid 1 has wire #2 and wire #9; solenoid 2 has wire #2 and wire #54.

**LP:** Solenoid 1 has wire #2 and wire #9; Solenoid 2 has wire #2 and wire #55; wire #56 is connected to a grounded wire #9.

### **To convert from NG to LP:**

- Replace the wire #54 with wire #55 (located in the wire loom).
- Locate wire 56 in the wire harness and connect it to a grounded wire #9.

### **To convert from LP to NG:**

- Replace the wire #55 with wire #54 (located in the wire loom).
- Locate wire #56 that is connected to a grounded wire #9, unplug from each other, isolate from other wires and return these to the wire loom.