

CPC Fault Code List

J1939 SPN	FMI	PID/SID	J1587	FLASH	SERVICE DESCRIPTION
70	2	PID	70	2112	Park Brake Status Not Plausible (Vehicle Moving)
70	13	SID	234	2112	J1939 Park Brake Switch Signal from Source #1 is missing
70	13	SID	234	2112	J1939 Park Brake Switch Signal from Source #2 is missing
70	13	SID	234	2112	J1939 Park Brake Switch Signal from Source #3 is missing
70	19	SID	234	2112	J1939 Park Brake Switch Signal from Source #1 is erratic
70	19	SID	234	2112	J1939 Park Brake Switch Signal from Source #2 is erratic
70	19	SID	234	2112	J1939 Park Brake Switch Signal from Source #3 is erratic
84	0	PID	84	2113	Vehicle Speed Above Programmable Threshold1 While Driving
84	2	PID	84	2113	VSS Anti Tamper Detection via Virtual Gear Ratio
84	3	PID	84	2113	Vehicle Speed Sensor Circuit Failed High
84	4	PID	84	2113	Vehicle Speed Sensor Circuit Failed Low
84	6	PID	84	2113	VSS Anti-Tamper Detection via ABS Vehicle Speed Comparison
84	8	PID	84	2113	VSS Anti Tamper Detection via Fixed Frequency Device
84	11	PID	84	2113	Vehicle Speed Above Programmable Threshold2 While Driving
84	13	PID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#1 is missing
84	13	PID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#2 is missing
84	13	PID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#3 is missing
84	19	PID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#1 is erratic
84	19	SID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#2 is erratic
84	19	PID	84	2113	J1939 Wheel-Based Vehicle Speed Signal from Source#3 is erratic
84	20	PID	84	2113	Vehicle Speed Sensor Drifted High Error (VSS signal not plausible)
84	21	PID	84	2113	Vehicle Speed Failure
91	3	PID	91	2114	Accelerator Pedal Circuit Failed High
91	3	PID	91	2114	Accelerator Pedal Signal Circuit Failed High
91	4	PID	91	2114	Accelerator Pedal Circuit Failed Low
91	7	PID	91	2114	Pwm Accelerator Pedal Idle Not Recognized
91	8	PID	91	2114	Pwm Accelerator Pedal Signal 1 Frequency Out Of Range
91	9	SID	231	2114	J1939 Retarder Fluid Message is missing
91	9	SID	231	2114	J1939 EEC2 Message is missing
91	13	PID	91	2114	Accelerator Pedal Learn Error
91	14	PID	91	2114	Pwm Accelerator Pedal Not Learned
91	31	PID	91	2114	Pwm Accelerator Pedal Learned Range to Large
98	0	PID	98	2115	Oil Level High
98	1	PID	98	2115	Oil Level Very Low

98	18	PID	98	2115	Oil Level Low
100	1	PID	100	2121	Oil Pressure Very Low
100	18	PID	100	2121	Oil Pressure Low
107	0	PID	107	2122	Air Filter Restriction High
110	0	PID	110	2123	Coolant Temperature Very High
110	16	PID	110	2123	Coolant Temperature High
111	1	PID	111	2124	Coolant Level Very Low
111	3	PID	111	2124	Coolant Level Circuit Failed High
111	4	PID	111	2124	Coolant Level Circuit Failed Low
111	18	PID	111	2124	Coolant Level Low
168	0	PID	168	2125	Battery Voltage Very Low
168	0	PID	168	2125	Battery Voltage High
168	14	PID	168	2125	Opt Idle Detected Charging System or Battery Failure
168	14	PID	168	2125	ECU powerdown not completed (Main Battery Terminal Possibly Floating)
168	18	PID	168	2125	Battery Voltage Low
171	2	PID	171	2131	Ambient Temperature Sensor Data Erratic
171	9	PID	171	2131	J1587 Ambient Air Temp Sensor Data Message Stopped Arriving
171	14	PID	171	2131	J1587 Ambient Air Temp Sensor Data Not Received This Ign Cycle
187	3	PID	187	0	Idle Volume Sensor Shorted to Battery
187	4	PID	187	0	Idle Volume Sensor Shorted to Ground
191	9	SID	231	2131	J1939 ETC1 Message is missing
191	13	SID	231	2132	J1939 Transmission Output Shaft Speed Signal is missing
191	19	SID	231	2132	J1939 Transmission Output Shaft Speed Signal is erratic
247	0	PID	247	2341	MCM Engine Hours Data higher than expected
247	1	PID	247	2341	MCM Engine Hours Data lower than expected
247	9	PID	247	2341	MCM Engine Hours Data not received or stopped arriving
247	10	PID	247	2341	MCM Engine Hours Data increasing at an implausible rate
247	14	PID	247	2411	MCM Reported Ash Mileage is Lower then the CPC Stored Value
523	13	PID	163	2133	J1939 Transmission Current Gear Signal is missing
523	19	PID	163	2133	J1939 Transmission Current Gear Signal is erratic
524	9	SID	231	2342	J1939 ETC2 Message is missing
527	9	SID	231	2343	J1939 CCVS Message from Source #1 is missing
527	9	SID	231	2343	J1939 CCVS Message from Source #2 is missing
527	9	SID	231	2343	J1939 CCVS Message from Source #3 is missing
558	2	SID	230	2134	Idle Validation Switch Inputs Reversed
558	3	SID	230	2134	Idle Validation Switch 1 Circuit Failed High
558	4	SID	230	2134	Idle Validation Switch 1 Circuit Failed Low

558	5	SID	230	2134	Idle Validation Switch 2 Circuit Failed Low
558	6	SID	230	2134	Idle Validation Switch 2 Circuit Failed High
596	13	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #1 is missing
596	13	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #2 is missing
596	13	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #3 is missing
596	19	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #1 is erratic
596	19	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #2 is erratic
596	19	SID	244	2135	J1939 Cruise Control Enable Switch Signal from Source #3 is erratic
597	2	SID	246	2141	Service Brake Status Not Plausible
597	13	SID	246	2141	J1939 Service Brake Switch Signal from Source #1 is missing
597	13	SID	246	2141	J1939 Service Brake Switch Signal from Source #2 is missing
597	13	SID	246	2141	J1939 Service Brake Switch Signal from Source #3 is missing
597	19	SID	246	2141	J1939 Service Brake Switch Signal from Source #1 is erratic
597	19	SID	246	2141	J1939 Service Brake Switch Signal from Source #2 is erratic
597	19	SID	246	2141	J1939 Service Brake Switch Signal from Source #3 is erratic
599	4	SID	243	2142	Cruise Control SET and RESUME Circuits Failed Low
600	13	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #1 is missing
600	13	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #2 is missing
600	13	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #3 is missing
600	19	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #1 is erratic
600	19	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #2 is erratic
600	19	SID	243	2143	J1939 Cruise Control Coast Switch Signal from Source #3 is erratic
602	13	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #1 is missing
602	13	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #2 is missing
602	13	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #3 is missing
602	19	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #1 is erratic
602	19	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #2 is erratic
602	19	SID	242	2144	J1939 Cruise Control Accelerate Switch Signal from Source #3 is erratic
608	14	SID	250	2145	J1708 Data Link Failure
609	12	SID	233	2145	CPC2 Hardware Failure
625	2	SID	248	2151	ECAN ID_1629 Diagnostic Message Reporting Data Not Available
625	4	SID	248	2151	ECAN Link Circuit Failure
625	9	SID	248	2151	ECAN ID_1629 Diagnostic Message No Longer Being Received
625	9	SID	248	2151	Incorrect MCM System ID Received
625	9	SID	248	2151	MCM System ID Not Received or Stopped Arriving
625	10	SID	248	2151	ECAN ID_1629 Reporting Inconsistent Number of Frames
625	13	SID	248	2151	ECAN ID_1629 Diagnostic Message Not Received This Ignition Cycle

625	14	SID	248	2151	ECAN ID_1629 Diagnostic Message Reporting an Unknown MUID
628	13	SID	155	2344	20ms ECU OS Task Locked in an Endless Loop
628	13	SID	155	2344	20ms ECU OS Task Timed out Prior to Completion
628	13	SID	155	2344	1000ms ECU OS Task Locked in an Endless Loop
628	13	SID	155	2344	1000ms ECU OS Task Timed out Prior to Completion
628	14	SID	254	2344	XFLASH Static Fault Code Memory Page Read Write Failure
629	2	SID	254	2151	CPC Hardware/Software Mismatch
629	12	SID	254	2151	DDEC Data Xflash Write Error. Replace CPC2.
630	2	SID	253	2152	EEPROM Checksum Failure
630	2	SID	253	2152	EEPROM Checksum Failure for the SCR Block
630	13	SID	253	2152	SCR Number Out of Range
630	14	SID	155	2152	MCM Fault Codes Unavailable via J1939 and J1587
630	14	SID	155	2152	MCM Fault Code Table Inconsistent - Upgrade MCM Software
630	14	SID	155	2152	Insufficient Static Fault Code Storage Memory - Upgrade CPC Software
630	14	SID	155	2152	MCM Fault Code Table Inconsistent - Upgrade MCM Software
639	9	PID	107	2244	J1939 PROP11 message is missing
639	14	SID	231	2153	J1939 Data Link Failure
701	3	SID	26	2211	Digital Output 4 09 Circuit Failed High
701	4	SID	26	2211	Digital Output 4 09 Circuit Failed Low
702	3	SID	40	2212	Digital Output 3 17 Circuit Failed High
702	4	SID	40	2212	Digital Output 3 17 Circuit Failed Low
703	3	SID	51	2213	Digital Output 3 09 Circuit Failed High
703	4	SID	51	2213	Digital Output 3 09 Circuit Failed Low
704	3	SID	52	2214	Digital Output 4 07 Circuit Failed High
704	4	SID	52	2214	Digital Output 4 07 Circuit Failed Low
705	3	SID	53	2215	Digital Output 1 13 Circuit Failed High
705	4	SID	53	2215	Digital Output 1 13 Circuit Failed Low
706	3	SID	54	2221	Digital Output 3 10 Circuit Failed High
706	4	SID	54	2221	Digital Output 3 10 Circuit Failed Low
707	3	SID	55	2222	Digital Output 2 10 Circuit Failed High (CEL / AWL Lamp)
707	4	SID	55	2222	Digital Output 2 10 Circuit Failed Low (CEL / AWL Lamp)
708	3	SID	56	2223	Digital Output 3 12 Circuit Failed High
708	4	SID	56	2223	Digital Output 3 12 Circuit Failed Low
709	3	SID	257	2224	Digital Output 3 16 Circuit Failed High
709	4	SID	257	2224	Digital Output 3 16 Circuit Failed Low
710	3	SID	258	2225	Digital Output 4 06 Circuit Failed High
710	4	SID	258	2225	Digital Output 4 06 Circuit Failed Low

711	3	SID	259	2231	Digital Output 1 05 Circuit Failed High
711	4	SID	259	2231	Digital Output 1 05 Circuit Failed Low
712	3	SID	260	2232	Digital Output 1 04 Circuit Failed High
712	4	SID	260	2232	Digital Output 1 04 Circuit Failed Low
713	3	SID	261	2234	Digital Output 3 07 Circuit Failed High
713	4	SID	261	2234	Digital Output 3 07 Circuit Failed Low
713	5	SID	261	2234	Digital Output 3 07 Open Circuit
713	7	SID	261	2234	TOP2 Shift Failure
714	3	SID	262	2235	Digital Output 3 08 Circuit Failed High
714	4	SID	262	2235	Digital Output 3 08 Circuit Failed Low
714	5	SID	262	2235	Digital Output 3 08 Open Circuit
715	3	SID	263	2241	Digital Output 4 10 Circuit Failed High
904	9	SID	231	2242	J1939 EBC2 Message from ABS is missing
904	13	SID	231	2242	J1939 Front Axle Speed Signal is missing
904	19	SID	231	2242	J1939 Front Axle Speed Signal is erratic
972	2	SID	203	2243	Throttle inhibit switch signal not plausible due to excess vehicle speed
973	9	SID	231	2244	J1939 EBC1 Message is missing
973	13	SID	231	2244	J1939 Engine Retarder Selection Signal Missing
973	19	SID	231	2244	J1939 Engine Retarder Selection Signal Erratic
974	2	PID	372	2245	Remote Accelerator Pedal Supply Voltage Out of Range
974	3	PID	372	2245	Remote Accelerator Pedal Circuit Failed High
974	4	PID	372	2245	Remote Accelerator Pedal Circuit Failed Low
979	9	SID	231	2412	J1939 PTO Message Not Received This Ignition Cycle
986	9	SID	231	2345	J1939 CM1 Message is missing
1267	3	SID	123	2312	Digital Output 4 10 Circuit Failed Open
1267	4	SID	123	2312	Digital Output 4 10 Circuit Failed Low
1590	9	SID	231	2351	Adaptive Cruise Control Device Reporting Error
1590	19	SID	155	2351	Adaptive Cruise Control Message Not Received
1624	9	SID	231	2315	J1939 TCO1 Message is missing
1624	13	SID	231	2315	J1939 Tachograph Vehicle Speed Signal is missing
1624	19	SID	231	2315	J1939 Tachograph Vehicle Speed Signal is erratic
1663	7	SID	123	2321	Optimized Idle Safety Loop Faulted
1716	9	SID	231	2352	J1939 ERC1 Message is missing
1845	9	SID	231	2353	J1939 TCFG2 Message is missing
2623	8	PID	91	2322	Pwm Accelerator Pedal Signal 2 Frequency Out Of Range
2623	14	PID	91	2322	Pwm Accelerator Pedal GAS1 and GAS2 Signal Missing
2900	9	SID	231	2354	J1939 ETC7 Message is missing

3510	3	SID	211	2333	Accelerator Pedal Supply Voltage Circuit Failed High
3510	3	SID	211	2333	Accelerator Pedal Supply Voltage Circuit Failed High
3510	4	SID	211	2333	Accelerator Pedal Supply Voltage Circuit Failed Low
3510	4	SID	211	2333	Pwm Accelerator Pedal Supply Voltage Missing
3606	9	SID	231	2355	J1939 ESS Message is missing
3695	9	SID	155	2334	DPF Regen Inhibit MUX Switch Message Stopped Arriving
3695	13	SID	155	2334	DPF Regen Inhibit MUX Switch Message Contains SNV Indicator
3695	14	SID	155	2334	DPF Regen Inhibit MUX Switch Message Not Received this Ign Cycle
3695	19	SID	155	2334	DPF Regen Inhibit MUX Switch Message Contains Data Error Indicator
3696	9	SID	155	2335	DPF Regen Force MUX Switch Message Stopped Arriving
3696	13	SID	155	2335	DPF Regen Force MUX Switch Message Contains SNV Indicator
3696	14	SID	155	2335	DPF Regen Force MUX Switch Message Not Received this Ign Cycle
3696	19	SID	155	2335	DPF Regen Force MUX Switch Message Contains Data Error Indicator